

# QuickSpecs

## Overview

---

### Models

HP X122 1G SFP LC BX-D Transceiver

J9142B

HP X122 1G SFP LC BX-U Transceiver

J9143B



# QuickSpecs

## HP X122 1G SFP LC Transceivers

### Technical Specifications

<p><b>HP X122 1G SFP LC BX-D Transceiver (J9142B)</b></p> <p>A small form-factor pluggable (SFP) Gigabit-BX (bi-directional) "downstream" transceiver that provides a full-duplex Gigabit solution up to 10 km on one strand of single-mode fiber. The J9142B connects to the J9143B "upstream" transceiver, or to any IEEE-standard 1000BASE-BX10-U ("upstream") device.</p>	<p><b>Ports</b></p> <p>1 LC 1000BASE-BX10 port (IEEE 802.3ah Type 1000BASE-BX10-D); Duplex: full only</p> <p><b>Physical characteristics</b></p> <p><b>Dimensions</b> 2.19(d) x 0.54(w) x 0.46(h) in. (5.57 x 1.37 x 1.18 cm)</p> <p><b>Weight</b> 0.04 lb. (0.02 kg)</p> <p><b>Environment</b></p> <p><b>Operating temperature</b> 32°F to 158°F (0°C to 70°C)</p> <p><b>Operating relative humidity</b> 0% to 95%, non-condensing</p> <p><b>Non-operating/Storage temperature</b> -40°F to 185°F -40°C to 85°C</p> <p><b>Cabling</b></p> <p>Type: Single-mode fiber optic, complying with ITU-T G.652;</p> <p>Maximum distance:</p> <ul style="list-style-type: none"> <li>● 0.5-10,000 m (single-mode fiber)</li> </ul> <p><b>Notes</b></p> <p>Transmit wavelength: 1490 nm. Receive wavelength: 1310 nm. Power consumption is 1 watt maximum. For supported platforms and minimum software requirements to support this product, see the document titled "Support for the HP BX Transceivers" on the "HP Mini-GBICs and SFPs" Manuals Web page. The J9142B connects to the J9143B "upstream" transceiver, or to any IEEE-standard 1000BASE-BX10-U ("upstream") device. (A 1000-BX-D transceiver can only connect to a 1000-BX-U product. You cannot connect two 1000-BX-D transceivers together.)</p> <p><b>Services</b></p> <p>Refer to the HP website at <a href="http://www.hp.com/networking/services">www.hp.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.</p>
---	---

<p><b>HP X122 1G SFP LC BX-U Transceiver (J9143B)</b></p> <p>A small form-factor pluggable (SFP) Gigabit-BX (bi-directional) "upstream" transceiver that provides a full-duplex Gigabit solution up to 10 km on one strand of single-mode fiber. The J9143B connects to the J9142B "downstream" transceiver, or to any IEEE-standard 1000BASE-BX10-D ("downstream") device.</p>	<p><b>Ports</b></p> <p>1 LC 1000BASE-BX10 port (IEEE 802.3ah Type 1000BASE-BX10-U); Duplex: full only</p> <p><b>Physical characteristics</b></p> <p><b>Dimensions</b> 2.19(d) x 0.54(w) x 0.46(h) in. (5.57 x 1.37 x 1.18 cm)</p> <p><b>Weight</b> 0.04 lb. (0.02 kg)</p> <p><b>Environment</b></p> <p><b>Operating temperature</b> 32°F to 158°F (0°C to 70°C)</p> <p><b>Operating relative humidity</b> 0% to 95%, non-condensing</p> <p><b>Non-operating/Storage temperature</b> -40°F to 185°F -40°C to 85°C</p> <p><b>Cabling</b></p> <p>Type: Single-mode fiber optic, complying with ITU-T G.652;</p> <p>Maximum distance:</p> <ul style="list-style-type: none"> <li>● 0.5-10,000 m (single-mode fiber)</li> </ul>
---	--



## Technical Specifications

<b>Notes</b>	<p>Transmit wavelength: 1310 nm. Receive wavelength: 1490 nm.</p> <p>For supported platforms and minimum software requirements to support this product, see the document titled "Support for the HP BX Transceivers" on the "HP Mini-GBICs and SFPs" Manuals Web page.</p> <p>The J9143B connects to the J9142B "downstream" transceiver, or to any IEEE-standard 1000BASE-BX10-D ("downstream") device. (A 1000-BX-U transceiver can only connect to a 1000-BX-D product. You cannot connect two 1000-BX-U transceivers together.)</p> <p>Power consumption is 1 watt maximum.</p>
<b>Services</b>	<p>Refer to the HP website at <a href="http://www.hp.com/networking/services">www.hp.com/networking/services</a> for details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local HP sales office.</p>

---

To learn more, visit [www.hp.com/networking](http://www.hp.com/networking)

© Copyright 2011 Hewlett-Packard Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

