

### Overview

## HPE Altoline 6920 Switch Series

### Models

HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Front-to-Back Switch	JL167A
HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Back-to-Front Switch	JL168A

### Key features

- High 10GbE port density and low latency for demanding applications.
- ONIE boot loader for choice of network OS and easy installation.
- OCP-certified, Open-networking and disaggregated solution for customer choice.
- VXLAN for efficient network virtualization overlay solutions.
- x86 CPU controller, redundant fans and power supplies for data center deployments.

### Product overview

The HPE Altoline 6920 Switch Series are top-of-rack (TOR) or spine switches for high-performance data centers. In a compact 1RU form factor, these switches provides line-rate L2 and L3 switching across up to 48 x SFP+ ports, with 6 x 40GbE QSFP+ uplink connections.

The HPE Altoline 6920 Switch Series can be deployed as a TOR switch supporting 10GbE server connections, or as a spine switch, supporting 10GbE interconnects.

The HPE Altoline 6920 Switch Series a bare-metal switches loaded with the Open Network Install Environment (ONIE), which supports the installation of compatible independent switch OS offerings.

### Features and benefits

#### Data center optimized

- **Flexible high port density**  
the HPE Altoline 6920 Switch Series enables scaling of the server edge with 10GbE server connection, with 40GbE uplinks, to new heights with high density delivered in a 1RU design.
- **High-performance switching**  
cut-through and nonblocking architecture delivers low latency (600 - 720 nanosecond for 40GbE) for very demanding enterprise applications; the switch delivers high-performance switching capacity and wire-speed packet forwarding
- **Hot/cold aisle support**  
models available with front-to-back (port-to-power) or back-to-front (power-to-port) airflow
- **Redundant fans and power supplies**  
1+1 internal redundant and hot-pluggable power supplies and N+1 redundant fan trays enhance reliability and availability
- **VXLAN hardware support**  
supports VXLAN VTEP overlay technologies

#### Manageability

- **Out-of-band interface**  
isolates management traffic from user data plane traffic for complete isolation and total reachability, no matter what happens in the data plane
- **ONIE bootloader**

## Overview

switch is loaded with Open Network Install Environment (ONIE) software installer

- **Intel x86 CPU**  
provides high performance support of widely available, industry standard software and utilities

## Layer 2 switching

- **VLAN support**  
provides support for 4,096 VLAN IDs

## Additional information

- **Low power consumption**  
typical operation uses just 267W of AC power

## Warranty and support

- **1-year Warranty**  
See <http://www.hpe.com/networking/warrantysummary> for warranty and support information included with your product purchase.
- **Software releases**  
to find software for your product, refer to <http://www.hpe.com/networking/support>; for details on the software releases available with your product purchase, refer to <http://www.hpe.com/networking/warrantysummary>

### Configuration

#### Build To Order:

BTO is a standalone unit with no integration. BTO products ship standalone are not part of a CTO or Rack-Shippable solution.

HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Front-to-Back Switch	JL167A
<ul style="list-style-type: none"><li>48 SFP/SFP+ 1/10GbE ports (min=0 \ max=48 SFP/SFP+ Transceivers)</li><li>6 QSFP+ 40GbE ports (min=0 \ max=6 QSFP+ Transceivers)</li></ul> Each Switch: <ul style="list-style-type: none"><li>2 Power Supplies Standard (min=2 \ max=2)</li><li>5 Front to Back Fan Trays Standard (min=5 \ max=5)</li><li>1U - Height</li></ul>	See Configuration <b>NOTE: 1, 2, 3, 5</b>
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"><li>C13 PDU Jumper Cord (NA/MEX/TW/JP)</li></ul>	JL167A#B2B
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"><li>C13 PDU Jumper Cord (ROW)</li></ul>	JL167A#B2C
High Volt Switch/Router to Wall Power Cord <ul style="list-style-type: none"><li>NEMA L6-20P Cord (NA/MEX/JP/TW)</li></ul>	JL167A#B2E
No Power Cord <ul style="list-style-type: none"><li>No Localized Power Cord Selected</li></ul>	JL167A#AC3
HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Back-to-Front Switch	JL168A
<ul style="list-style-type: none"><li>48 SFP/SFP+ 1/10GbE ports (min=0 \ max=48 SFP/SFP+ Transceivers)</li><li>6 QSFP+ 40GbE ports (min=0 \ max=6 QSFP+ Transceivers)</li></ul> Each Switch: <ul style="list-style-type: none"><li>2 Power Supplies Standard (min=2 \ max=2)</li><li>5 Back to Front Fan Trays Standard (min=5 \ max=5)</li><li>1U - Height</li></ul>	See Configuration <b>NOTE: 1, 2, 3, 5</b>
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"><li>C15 PDU Jumper Cord (NA/MEX/TW/JP)</li></ul>	JL168A#B2B
PDU Cable NA/MEX/TW/JP <ul style="list-style-type: none"><li>C15 PDU Jumper Cord (ROW)</li></ul>	JL168A#B2C
High Volt Switch/Router to Wall Power Cord <ul style="list-style-type: none"><li>NEMA L6-20P Cord (NA/MEX/JP/TW)</li></ul>	JL168A#B2E
No Power Cord <ul style="list-style-type: none"><li>No Localized Power Cord Selected</li></ul>	JL168A#AC3

#### Configuration Rules:

## Configuration

<b>Note 1</b>	Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord) or #B2E. (See Localization Menu)	
<b>Note 2</b>	The following QSFP+ Transceivers install into this Switch:	
	HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
	HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
	HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
	HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
	HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
<b>Note 3</b>	The following SFP/SFP+ Transceivers install into this Switch	
	HPE X120 1G SFP RJ45 T Transceiver	JD089B
	HPE X120 1G SFP LC SX Transceiver	JD118B
	HPE X120 1G SFP LC LX Transceiver	JD119B
	HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
	HPE X130 10G SFP+ LC SR Transceiver	JD092B
	HPE X130 10G SFP+ LC LR Transceiver	JD094B
	HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
	HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
	HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
	HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
	HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
	HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C
<b>Note 5</b>	The following DAC Splitter Cables install into this Switch:	
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
	HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

## Rack Level Integration CTO Models

### CTO Switch Chassis

- HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Front-to-Back Switch
- 48 SFP+ 1/10GbE ports (min=0 \ max=48 SFP+ Transceivers)
  - 6 QSFP+ 40GbE ports (min=0 \ max=6 QSFP+ Transceivers)  
Each Switch:
  - 2 Power Supplies Standard (min=2 \ max=2)
  - 5 Front to Back Fan Trays Standard (min=5 \ max=5)
  - 1U - Height

JL167A  
See Configuration  
**NOTE: 1, 2, 3, 5**

PDU Cable NA/MEX/TW/JP

- C13 PDU Jumper Cord (NA/MEX/TW/JP)

JL167A#B2B

## Configuration

PDU Cable NA/MEX/TW/JP	JL167A#B2C
<ul style="list-style-type: none"> <li>C13 PDU Jumper Cord (ROW)</li> </ul>	
High Volt Switch/Router to Wall Power Cord	JL167A#B2E
<ul style="list-style-type: none"> <li>NEMA L6-20P Cord (NA/MEX/JP/TW)</li> </ul>	
HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Back-to-Front Switch	JL168A
<ul style="list-style-type: none"> <li>48 SFP+ 1/10GbE ports (min=0 \ max=48 SFP+ Transceivers)</li> <li>6 QSFP+ 40GbE ports (min=0 \ max=6 QSFP+ Transceivers)</li> </ul> Each Switch:	See Configuration
<ul style="list-style-type: none"> <li>2 Power Supplies Standard (min=2 \ max=2)</li> <li>5 Back to Front Fan Trays Standard (min=5 \ max=5)</li> <li>1U - Height</li> </ul>	<b>NOTE: 1, 2, 3, 5</b>
PDU Cable NA/MEX/TW/JP	JL168A#B2B
<ul style="list-style-type: none"> <li>C13 PDU Jumper Cord (NA/MEX/TW/JP)</li> </ul>	
PDU Cable NA/MEX/TW/JP	JL168A#B2C
<ul style="list-style-type: none"> <li>C13 PDU Jumper Cord (ROW)</li> </ul>	
High Volt Switch/Router to Wall Power Cord	JL168A#B2E
<ul style="list-style-type: none"> <li>NEMA L6-20P Cord (NA/MEX/JP/TW)</li> </ul>	

### Configuration Rules:

**Note 1**      Localization (Wall Power Cord) required on orders without #B2B, #B2C (PDU Power Cord) or #B2E. (See Localization Menu)

**Note 2**      The following QSFP+ Transceivers install into this Switch:

HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

**Note 3**      The following SFP/SFP+ Transceivers install into this Switch

HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A
HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A

## Configuration

HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C

**Note 5**      **The following DAC Splitter Cables install into this Switch:**

HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

## Transceivers

### SFP Transceivers

HPE X120 1G SFP RJ45 T Transceiver	JD089B
HPE X120 1G SFP LC SX Transceiver	JD118B
HPE X120 1G SFP LC LX Transceiver	JD119B
HPE X120 1G SFP LC LH40 1550nm Transceiver	JD062A

### SFP+ Transceivers

HPE X130 10G SFP+ LC SR Transceiver	JD092B
HPE X130 10G SFP+ LC LR Transceiver	JD094B
HPE X130 10G SFP+ LC SR Data Center Transceiver	JL437A
HPE X130 10G SFP+ LC LR Data Center Transceiver	JL439A
HPE X130 10G SFP+ LC LH 80km Transceiver	JG915A
HPE FlexNetwork X240 10G SFP+ to SFP+ 0.65m Direct Attach Copper Cable	JD095C
HPE FlexNetwork X240 10G SFP+ to SFP+ 1.2m Direct Attach Copper Cable	JD096C
HPE FlexNetwork X240 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	JD097C
HPE FlexNetwork X240 10G SFP+ to SFP+ 5m Direct Attach Copper Cable	JG081C
HPE FlexNetwork X240 10G SFP+ SFP+ 7m Direct Attach Copper Cable	JC784C

### QSFP+ Transceivers

HPE X140 40G QSFP+ LC BiDi 100m MM Transceiver	JL251A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A

## Switch Enclosure Options

## Configuration

### Rack Mount Kit

System (std 0 // max 1) User Selection (min 0 // max 1)

HPE Altoline Gen2 Rackmount Kit

JL198A  
See Configuration  
**NOTE: 1, 3**

### Configuration Rules:

#### Note 1

This rack mount kit is only supported on the following switches:

HPE Altoline 6940 32QSFP+ x86 ONIE AC Front-to-Back Switch	JL165A
HPE Altoline 6940 32QSFP+ x86 ONIE AC Back-to-Front Switch	JL166A
HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Front-to-Back Switch	JL167A
HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Back-to-Front Switch	JL168A
HPE Altoline 6960 32QSFP28 x86 ONIE AC Front-to-Back Switch	JL279A
HPE Altoline 6960 32QSFP28 x86 ONIE AC Back-to-Front Switch	JL280A

#### Note 3

If a switch is ordered and factory racked, then this rackmount must be #OD1

## Technical Specifications

### HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Front-to-Back Switch (JL167A)

<b>I/O ports and slots</b>	48 SFP+ 1/10GbE ports (IEEE 802.3ae Type 10GBASE-ER, IEEE 802.3ae Type 10GBASE-LR, IEEE 802.3ae Type 10GBASE-SR, IEEE 802.3z Type 1000BASE-SX, IEEE 802.3z Type 1000BASE-LX) 6 QSFP+ 40GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0	
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required includes: 2 x PSUs ○	
<b>Fan tray</b>	5 fan tray slots Switch comes with five (5) fan trays (port to power airflow)	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 18.5(d) x 1.72(h) in (44.00 x 47.0 x 4.4 cm)
	<b>Weight</b>	18.52 lb (8.4 kg)
<b>Memory and processor</b>	Intel Atom C2538 quad-core x86 processor @ 2.4 GHz, 8 GB DDR3 SDRAM; Packet buffer size: 12 MB, 16 GB SD Card	
<b>Performance</b>	<b>40 Gbps Latency</b>	> .6 μs
	<b>Throughput</b>	up to 1 Bpps
	<b>Routing/Switching capacity</b>	1440 Gbps
	<b>Routing table size</b>	64000 entries (IPv4), 20000 entries (IPv6)
	<b>MAC address table size</b>	320000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 104°F (0°C to 40°C)
	<b>Operating relative humidity</b>	5% to 95%, noncondensing
	<b>Nonoperating/Storage temperature</b>	-40°F to 158°F (-40°C to 70°C)
<b>Electrical characteristics</b>	<b>Frequency</b>	50/60 Hz
	<b>Voltage</b>	90 - 264 VAC, rated
	<b>Maximum power rating</b>	315 W
	<b>Idle power</b>	267 W
	<b>Notes</b>	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated. PSU Efficiency: Up to 93% for AC PSUs
<b>Safety</b>	cUL Certified; EN 60950; EN 55022 Class A; VCCI Class A; ROHS Compliance; FCC Class A: Regulations for Radio Frequency Devices for Electromagnetic Compliance; UL	
<b>Emissions</b>	FCC part 15 Class A; EN 55022 Class A; VCCI	
<b>Immunity</b>	<b>ESD</b>	EN 60950
	<b>EFT/Burst</b>	IEC 68-2-14
<b>Management</b>	Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise sales website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> or details on the service-level descriptions and product numbers. For details about services and	



## Technical Specifications

response times in your area, please contact your local Hewlett Packard Enterprise sales office.

### HPE Altoline 6920 48XG 6QSFP+ x86 ONIE AC Back-to-Front Switch (JL168A)

<b>I/O ports and slots</b>	48 SFP+ 1/10GbE ports (IEEE 802.3ae Type 10GBASE-ER, IEEE 802.3ae Type 10GBASE-LR, IEEE 802.3ae Type 10GBASE-SR, IEEE 802.3z Type 1000BASE-SX, IEEE 802.3z Type 1000BASE-LX) 6 QSFP+ 40GbE ports	
<b>Additional ports and slots</b>	1 RJ-45 serial console port 1 RJ-45 out-of-band management port 1 USB 2.0	
<b>Power supplies</b>	2 power supply slots 1 minimum power supply required includes: 2 x PSUs ()	
<b>Fan tray</b>	5 fan tray slots Switch comes with five (5) fan trays (power to port airflow)	
<b>Physical characteristics</b>	<b>Dimensions</b>	17.32(w) x 18.5(d) x 1.72(h) in (44.00 x 47.0 x 4.4 cm)
	<b>Weight</b>	18.52 lb (8.4 kg)
<b>Memory and processor</b>	Intel Atom C2538 quad-core x86 processor @ 2.4 GHz, 8 GB DDR3 SDRAM; Packet buffer size: 12 MB, 16 GB SD Card	
<b>Performance</b>	<b>40 Gbps Latency</b>	> .6 $\mu$ s
	<b>Throughput</b>	up to 1 Bpps
	<b>Routing/Switching capacity</b>	1440 Gbps
	<b>Routing table size</b>	64000 entries (IPv4), 20000 entries (IPv6)
	<b>MAC address table size</b>	320000 entries
<b>Environment</b>	<b>Operating temperature</b>	32°F to 104°F (0°C to 40°C)
	<b>Operating relative humidity</b>	5% to 95%, noncondensing
	<b>Nonoperating/Storage temperature</b>	-40°F to 158°F (-40°C to 70°C)
<b>Electrical characteristics</b>	<b>Frequency</b>	50/60 Hz
	<b>Voltage</b>	90 - 264 VAC, rated
	<b>Maximum power rating</b>	315 W
	<b>Idle power</b>	267 W
	<b>Notes</b>	Idle power is the actual power consumption of the device with no ports connected. Maximum power rating and maximum heat dissipation are the worst-case theoretical maximum numbers provided for planning the infrastructure with fully loaded PoE (if equipped), 100% traffic, all ports plugged in, and all modules populated. PSU Efficiency: Up to 93% for AC PSUs
<b>Safety</b>	cUL Certified; EN 60950; EN 55022 Class A; VCCI Class A; ROHS Compliance; FCC Class A: Regulations for Radio Frequency Devices for Electromagnetic Compliance; UL	
<b>Emissions</b>	FCC part 15 Class A; EN 55022 Class A; VCCI	
<b>Immunity</b>	<b>ESD</b>	EN 60950
	<b>EFT/Burst</b>	IEC 68-2-14
<b>Management</b>	Command-line interface; Out-of-band management; SNMP manager; Telnet; FTP	
<b>Services</b>	Refer to the Hewlett Packard Enterprise sales website at: <a href="http://www.hpe.com/networking/services">http://www.hpe.com/networking/services</a> or details on the service-level descriptions and product numbers. For details about services and response times in your area, please contact your local Hewlett Packard Enterprise sales office.	

---

## Accessories

### HPE Altoline 6920 Switch Series accessories

#### Transceivers

HPE FlexNetwork X240 40G QSFP+ QSFP+ 1m Direct Attach Copper Cable	JG326A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 3m Direct Attach Copper Cable	JG327A
HPE FlexNetwork X240 40G QSFP+ QSFP+ 5m Direct Attach Copper Cable	JG328A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 1m Direct Attach Copper Splitter Cable	JG329A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 3m Direct Attach Copper Splitter Cable	JG330A
HPE FlexNetwork X240 40G QSFP+ to 4x10G SFP+ 5m Direct Attach Copper Splitter Cable	JG331A
HPE X140 40G QSFP+ LC LR4 SM 10km 1310nm Transceiver	JG661A
HPE X140 40G QSFP+ MPO SR4 Transceiver	JG325B
HPE X140 40G QSFP+ MPO MM 850nm CSR4 300m Transceiver	JG709A

## Summary of Changes

Date	Version History	Action	Description of Change
18-Apr-2017	Form Version 8 to 9	Added	Transceivers added on the Configuration section: JL437A, JL439A
23-Sep-2016	From Version 7 to 8	Changed	Warranty and support updated.
01-Aug-2016	From Version 6 to 7	Changed	Several updates on Configuration section including the addition of the #AC3 Option  Minor changes made in Technical Specifications.
15-Apr-2016	From Version 5 to 6	Changed	SKU descriptions updated (Accessories), Configuration section updated
18-Mar-2016	From Version 4 to 5	Changed	Product Number Descriptions updated  Configuration section added
16-Feb-2016	From Version 3 to 4	Changed	QuickSpecs name changed from HPE Altoline 5712 Switch Series to HPE Altoline 6920 Switch Series
08-Jan-2016	From Version 2 to 3	Changed	Warranty and support updated
17-Jul-2015	From Version 1 to 2	Changed	Error fixed on Product Overview



**Sign up for updates**



© Copyright 2017 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: <http://www.hpe.com/networking>

c04680998 - 15280 - Worldwide - V9 - 18-April-2017